

Diffraction-Attenuation Resistant Beams in Absorbing Media^(†)

Michel Zamboni-Rached,

DMO-FEEC, State University at Campinas, Campinas, SP, Brazil.

Abstract

In this work, in terms of suitable superpositions of equal-frequency Bessel beams, we develop a theoretical method to obtain nondiffractive beams in (weakly conductive) *absorbing media* capable to resist the loss effects for long distances.

PACS nos.: 41.20.Jb ; 03.50.De ; 03.30.+p ; 84.40.Az ; 42.82.Et ; 83.50.Vr ; 62.30.+d ; 43.60.+d ; 91.30.Fn ; 04.30.Nk ; 42.25.Bs ; 46.40.Cd ; 52.35.Lv .

1 Introduction

Over many years, the theory of nondiffracting beams and pulses has been developed, generalized and experimentally verified in many fields, such as optics, microwaves and acoustics[1-11].

When propagating in a non-absorbing medium, these waves maintain their spatial shape for long distances, i.e., they possess a large depth of field.

However, the situation is not the same when dealing with absorbing media. In these cases, both the ordinary and the nondiffracting beams (and pulses) will suffer the same effect: an exponential attenuation along the propagation axis.

Here, we are going to show that, through suitable superpositions of equal-frequency Bessel beams, it is possible to obtain nondiffracting beams *in absorbing media* capable to resist the loss effects, maintaining amplitude and spot size of their central core for long distances.

^(†) Work partially supported by FAPESP (Brazil).

E-mail address for contacts: mzamboni@dmo.fee.unicamp.br

The method that will be developed here is a generalization of a previous one (also developed by us)[12, 13], which was conceived for lossless media, where suitable superpositions of Bessel beams are used to construct *stationary* wave fields with arbitrary longitudinal intensity shape. Those new solutions were called Frozen Waves.

Before continuing, some points are to be stressed: (a) the method developed here addresses to poorly conductive media ($\sigma/\varepsilon\omega \ll 1$) in the optical frequency range; actually, we are considering materials where the penetration depth of the optical beams are typically $> 10^{-4}\text{m}$; (b) the energy absorption by the medium continues to occur normally, the difference being in that these new beams have an initial transverse field distribution, such to be able to reconstruct (even in the presence of absorption) their central cores for distances considerably longer than the penetration depths of ordinary (nondiffracting or diffracting) beams.

In the next Section we shall extend the previous method[12, 13] to absorbing media. Section 3 is devoted to obtaining examples of these new beams in some interesting situations.

2 The Mathematical Methodology

The method that will be developed in this Section is based on Bessel beams superpositions; so, it is appropriate first to recall some characteristics of such beams in absorbing media.

In the same way as for lossless media, we construct a Bessel beam in the absorbing materials by superposing plane waves whose wave vectors lie on the surface of a cone with vertex angle θ . The refractive index of the medium can be written as $n(\omega) = n_R(\omega) + in_I(\omega)$, quantity n_R being the real part of the complex refraction index and n_I the imaginary one, responsible for the absorbing effects. With a plane wave, the penetration depth δ for the frequency ω_0 is given by $\delta = c/2\omega_0 n_I$.

In this way, a zero-order Bessel beam in dissipative media can be written as

$\psi = J_0(k_\rho \rho) \exp(i\beta z) \exp(-i\omega t)$ with $\beta = n(\omega)\omega \cos \theta / c = n_R \omega \cos \theta / c + i n_I \omega \cos \theta / c \equiv \beta_R + i\beta_I$; $k_\rho = n_R \omega \sin \theta / c + i n_I \omega \sin \theta / c \equiv k_{\rho R} + i k_{\rho I}$, and so $k_\rho^2 = n^2 \omega^2 / c^2 - \beta^2$. In this way $\psi = J_0((k_{\rho R} + i k_{\rho I})\rho) \exp(i\beta_R z) \exp(-i\omega t) \exp(-\beta_I z)$, where β_R , $k_{\rho R}$ are the real parts of the longitudinal and transverse wave numbers, and β_I , $k_{\rho I}$ are the imaginary ones, while the absorption coefficient of a Bessel beam with an axicon angle θ is given by $\alpha_\theta = 2\beta_I = 2n_I \omega \cos \theta / c$, its penetration depth being $\delta = 1/\alpha = c/2\omega n_I \cos \theta$.

Due to the fact that k_ρ is complex, the amplitude of the Bessel function $J_0(k_\rho \rho)$ starts decreasing from $\rho = 0$ till the transverse distance $\rho = 1/2k_{\rho I}$, and afterwards it starts growing exponentially. This behavior is not physically acceptable, but one must remember that it occurs only because of the fact that an ideal Bessel beam needs an infinite aperture to be generated. However, in any real situation, when a Bessel beam is generated by finite apertures, that exponential growth in the transverse direction, starting after $\rho = 1/2k_{\rho I}$, will *not* occur indefinitely, stopping at a given value of ρ . Actually, taking into account the size of the aperture generally used for generating optical Bessel beams, and the fact that we are considering media that are poor conductors, that exponential growth does not even happen, and the resulting Bessel beam only presents a decreasing intensity in the transverse direction.

Let us now present our method.

Consider an absorbing medium with the complex refraction index $n(\omega) = n_R(\omega) + i n_I(\omega)$, and the following superposition of $2N + 1$ Bessel beams with the same frequency ω_0

$$\Psi(\rho, z, t) = \sum_{m=-N}^N A_m J_0((k_{\rho R_m} + i k_{\rho I_m})\rho) e^{i\beta_{R_m} z} e^{-i\omega_0 t} e^{-\beta_{I_m} z}, \quad (1)$$

where m are integer numbers, A_m are constant (yet unknown) coefficients, β_{R_m} and $k_{\rho R_m}$ (β_{I_m} and $k_{\rho I_m}$) are the real parts (the imaginary parts) of the complex longitudinal and transverse wave numbers of the m -th Bessel beam in superposition (1), the following

relations being satisfied

$$k_{\rho m}^2 = n^2 \frac{\omega^2}{c^2} - \beta_m^2 \quad (2)$$

$$\frac{\beta_{R_m}}{\beta_{I_m}} = \frac{n_R}{n_I} \quad (3)$$

$$\frac{k_{\rho R_m}}{k_{\rho I_m}} = \frac{n_R}{n_I} \quad (4)$$

where $\beta_m = \beta_{R_m} + i\beta_{I_m}$ and $k_{\rho m} = k_{\rho R_m} + ik_{\rho I_m}$.

Our goal is now to find out the values of the longitudinal wave numbers β_m and the coefficients A_m in order to reproduce approximately, inside the interval $0 \leq z \leq L$ (on the axis $\rho = 0$), a *freely chosen* longitudinal intensity pattern that we call $|F(z)|^2$.

The problem was already solved by us and the method developed for the particular case of lossless media[12, 13], i.e., when $n_I = 0 \rightarrow \beta_{I_m} = 0$. For those cases, it was shown that the choice $\beta = Q + 2\pi m/L$, with $A_m = \int_0^L F(z) \exp(-i2\pi m z/L)/L dz$ can be used to provide approximately the desired longitudinal intensity pattern $|F(z)|^2$ on the propagation axis, within the interval $0 \leq z \leq L$, and, at same time, to regulate the spot size of the resulting beam by means of the parameter Q , which can be also used to obtain large field depths (see details in Refs.[12, 13]).

However, when dealing with absorbing media, the procedure described in the last paragraph does not work, due to the presence of the functions $\exp(-\beta_{I_m} z)$ in the superposition (1), since in this case that series does not became a Fourier series when $\rho = 0$.

On attempting to overcome this limitation, let us write the real part of the longitudinal wave number, in superposition (1), as

$$\beta_{R_m} = Q + \frac{2\pi m}{L} \quad (5)$$

with

$$0 \leq Q + \frac{2\pi m}{L} \leq n_R \frac{\omega_0}{c} \quad (6)$$

where this inequality guarantees forward propagation only, with no evanescent waves.

In this way the superposition (1) can be written

$$\Psi(\rho, z, t) = e^{-i\omega_0 t} e^{iQz} \sum_{m=-N}^N A_m J_0((k_{\rho R_m} + ik_{\rho I_m})\rho) e^{i\frac{2\pi m}{L}z} e^{-\beta_{I_m}z}, \quad (7)$$

where, by using Eqs.(3), quantity β_{I_m} is given by

$$\beta_{I_m} = \frac{n_I}{n_R} \beta_{R_m} = \frac{n_I}{n_R} \left(Q + \frac{2\pi m}{L} \right) \quad (8)$$

and $k_{\rho m} = k_{\rho R_m} + ik_{\rho I_m}$ is given by Eq.(2).

Now, let us examine the imaginary part of the longitudinal wave numbers. From Eq.(8) the minimum and maximum values among the β_{I_m} are $(\beta_I)_{\min} = (Q - 2\pi N/L)n_I/n_R$ and $(\beta_I)_{\max} = (Q + 2\pi N/L)n_I/n_R$, the central one being given by $\bar{\beta}_I \equiv (\beta_I)_{m=0} = Qn_I/n_R$. With this in mind, let us evaluate the ratio

$$\Delta = \frac{(\beta_I)_{\max} - (\beta_I)_{\min}}{\bar{\beta}_I} = \frac{4\pi N}{LQ}. \quad (9)$$

Thus, when $\Delta \ll 1$, there are no considerable differences among the various β_{I_m} , since it holds $\beta_{I_m} \approx \bar{\beta}_I$ for all m . And, in the same way, there are no considerable differences among the exponential attenuation factors, since $\exp(-\beta_{I_m}z) \approx \exp(-\bar{\beta}_I z)$. So, when $\rho = 0$ the series in the r.h.s. of Eq.(7) can be approximately considered a truncated Fourier series *multiplied by* the function $\exp(-\bar{\beta}_I z)$: and, therefore, superposition (7) can be used to reproduce approximately the desired longitudinal intensity pattern $|F(z)|^2$ (on $\rho = 0$), within $0 \leq z \leq L$, when the coefficients A_m are given by

$$A_m = \frac{1}{L} \int_0^L F(z) e^{\bar{\beta}_I z} e^{-i \frac{2\pi m}{L} z} dz \quad (10)$$

the presence of the factor $\exp(\bar{\beta}_I z)$ in the integrand being necessary to compensate for the factors $\exp(-\beta_{Im} z)$ in superposition (7).

Since we are adding together zero-order Bessel functions, we can expect a good field concentration around $\rho = 0$.

In short, we have shown in this Section how one can get, in a weakly conductive *absorbing medium*, a *stationary* wave-field with a good transverse concentration, and whose longitudinal intensity pattern (on $\rho = 0$) can approximately assume any desired shape $|F(z)|^2$ within the predetermined interval $0 \leq z \leq L$. The method is a generalization of a previous one[12, 13] and consists in the superposition of Bessel beams in (7), the real and imaginary parts of their longitudinal wave numbers being given by Eqs.(5) and (8), while their complex transverse wave numbers are given by Eq.(2), and, finally, the coefficients of the superposition are given by Eq.(10). The method is justified, since $4\pi N/LQ \ll 1$; happily enough, this condition is satisfied in a great number of situations.

In the next Section we shall apply this method for obtaining new beams whose central core can resist the effects caused by diffraction and attenuation in absorbing media for long distances.

3 Examples: Almost Undistorted Beams in Absorbing Media

Let us consider a biological tissue as the absorbing medium. In the wavelength range 280 – 300nm, proteins are the major absorbers, being the UV absorption similar for many types of tissues.

A typical XeCl excimer laser ($\lambda = 308\text{nm} \rightarrow \omega = 6.09 \times 10^{15}\text{Hz}$) has a penetration depth, in this case, of 5 cm; i.e., an absorption coefficient $\alpha = 20\text{m}^{-1}$, and therefore

$n_I = 0.49 \times 10^{-6}$. The real part of the refraction index for this wavelength can be approximated by $n_R = 1.5$, and therefore $n = n_R + in_I = 1.5 + i 0.49 \times 10^{-6}$.

A typical Bessel beam with $\omega_0 = 6.09 \times 10^{15} \text{Hz}$ and with an axicon angle $\theta = 0.0141 \text{rad}$ (so, with a transverse spot of radius $8.4 \mu\text{m}$), when generated by an aperture, say, of radius $R = 3.5 \text{ mm}$, can propagate in vacuum a distance (its field depth) equal to $Z = R / \tan \theta = 25 \text{ cm}$ while resisting the diffraction effects. However, in the material medium considered here, the penetration depth of this Bessel beam would be only $z_p = 5 \text{ cm}$.

Now, we can use the method of the previous Section to obtain, in the same medium and for the same wavelength, an almost undistorted beam capable of preserving its spot size and the intensity of its *central core* for a distance many times larger than the typical penetration depth of an ordinary beam (nondiffracting or not).

With this purpose, let us suppose that, for this material medium, we want a beam (with $\omega_0 = 6.09 \times 10^{15} \text{Hz}$) that maintains amplitude and spot size of its central core for a distance of 25 cm , i.e., a distance 5 times greater than the penetration depth of an ordinary beam with the same frequency. We can model this beam by choosing the desired longitudinal intensity pattern $|F(z)|^2$ (on $\rho = 0$), within $0 \leq z \leq L$,

$$F(z) = \begin{cases} 1 & \text{for } 0 \leq z \leq Z \\ 0 & \text{elsewhere,} \end{cases} \quad (11)$$

and by putting $Z = 25 \text{ cm}$, with, for example, $L = 33 \text{ cm}$.

Now, the Bessel beam superposition (7) can be used to reproduce approximately this intensity pattern, and to this purpose let us choose $Q = 0.9999\omega_0/c$ for the β_{R_m} in Eq.(5), and $N = 20$ (which is allowed by inequality (6)).

Once we have chosen the values of Q , L and N , the values of the complex longitudinal and transverse Bessel beams wave numbers happen to be defined by relations (5), (8) and (2). Eventually, we can use Eq.(10) and find out the coefficients A_m of the fundamental superposition (7), that defines the resulting stationary wave-field.

Let us just note that the condition $4\pi N/LQ \ll 1$ is perfectly satisfied in this case.

In Fig.1(a) we compare the desired longitudinal intensity function $|F(z)|^2$ with the resulting stationary wave field, obtained from the Bessel beam superposition (7), and we can notice a good agreement between them. A better result could be reached by using a higher value of N , which in this specific example may assume, according to inequality (6), a maximum value of 158.

It is interesting to note that. at this distance (25 cm), an ordinary beam would have got its initial field-intensity attenuated 148 times.




Figure 1: Comparison between the intensity of the desired longitudinal function $F(z)$ (solid line) and that obtained from the Bessel beam superposition (7) (dotted line). One can observe a good agreement between them.

Figure 2(a) shows the 3D field-intensity of the resulting beam. One can see that the field possesses a good transverse localization (with a spot size smaller than $10\mu\text{m}$), it being capable of maintaining spot size and *intensity* of its central core till the desired distance. Figure 2(b) shows the same picture, but in an orthogonal projection.




Figure 2: **(a)** Three-dimensional field-intensity of the resulting beam. **(b)** The same figure in orthogonal projection.

As we have said in the Introduction, the energy absorption by the medium continues to occur normally; the difference is that these new beams have an initial transverse field distribution sophisticated enough to be able to reconstruct (even in the presence of absorption) their central cores till a certain distance. For a better visualization of this field-intensity distribution and of the energy flux, Fig.3(a) shows the resulting beam, in an orthogonal projection and in logarithmic scale. It is clear that the energy comes from the lateral regions, in order to reconstruct the central core of the beam. Figure 3(b) presents the initial field-intensity distribution on the aperture plane, at $z = 0$. We can note the complicated initial transverse field-intensity distribution needed for feeding the central core of the beam along the propagation axis.

Obviously, the amount of energy necessary to construct these new beams is greater than that necessary to generate an ordinary beam in a non-absorbing medium.




Figure 3: **(a)** The resulting beam, in an orthogonal projection and in logarithmic scale. **(b)** Initial field-intensity distribution on the aperture plane, at $z = 0$.

And it is also clear that there is a *limitation* on the depth of field of these new beams. For distances longer than 8 or 10 times the penetration depth of an ordinary beam, besides a great energy demand, we meet the fact that the field-intensity in the lateral regions would be even higher than that of the core, and the field would loose the usual characteristics of a beam (transverse field concentration).

4 Conclusion

In this paper we have shown that it is possible to construct almost-undistorted beams in absorbing media. They are got by suitable Bessel beams superpositions, and are capable to resist the loss effects, maintaining amplitude and spot size of their central core for long distances, when compared with the usual penetration depths of ordinary beams.

5 Acknowledgements

The author is very grateful to Erasmo Recami, Hugo E. Hernández-Figueroa and Claudio Conti for continuous discussions and kind collaboration.

References

- [1] J. Durnin, J. J. Miceli and J. H. Eberly, “Diffraction-free beams,” *Physical Review Letters* **58**, 1499-1501 (1987).
- [2] I. M. Besieris, A. M. Shaarawi and R. W. Ziolkowski, “A bi-directional traveling plane wave representation of exact solutions of the scalar wave equation,” *J. Math. Phys.* **30**, 1254-1269 (1989).
- [3] J.-Y. Lu and J. F. Greenleaf, “Nondiffracting X-waves: Exact solutions to free-space scalar wave equation and their finite aperture realizations,” *IEEE Trans. Ultrason. Ferroelectr. Freq. Control* **39**, 19-31 (1992).
- [4] P. Saari and K. Reivelt, “Evidence of X-shaped propagation-invariant localized light waves,” *Phys. Rev. Lett.* **79**, 4135-4138 (1997).
- [5] E. Recami, “On localized X-shaped Superluminal solutions to Maxwell equations”, *Physica A* **252**, 586-610 (1998), and refs. therein.
- [6] D. Mugnai, A. Ranfagni and R. Ruggeri, “Observation of superluminal behaviors in wave propagation,” *Phys. Rev. Lett.* **84**, 4830-4833 (2000). This paper aroused some criticisms, to which the authors replied.
- [7] M. Zamboni-Rached, E. Recami and H. E. Hernández-Figueroa, “New localized Superluminal solutions to the wave equations with finite total energies and arbitrary frequencies,” *European Physical Journal D* **21**, 217-228 (2002).

- [8] For a review, see: E. Recami, M. Zamboni-Rached, K. Z. Nóbrega, C. A. Dartora, and H. E. Hernández-Figueroa, “On the localized superluminal solutions to the Maxwell equations,” *IEEE Journal of Selected Topics in Quantum Electronics* **9**, 59-73 (2003), and refs. therein.
- [9] S. Longhi, “Spatial-temporal Gauss-Laguerre waves in dispersive media”, *Physical Review E*, **68**, article no.066612 (2003).
- [10] M. A. Porras, S. Trillo, C. Conti, and P. Di Trapani, “Paraxial envelope X waves”, *Optics Letters*, **28**, 1090-1093 (2003).
- [11] C. Conti, and S. Trillo, “X waves generated at the second harmonic”, *Optics Letters*, **28**, 1251-1253 (2003).
- [12] M. Zamboni-Rached, “Stationary optical wave fields with arbitrary longitudinal shape by superposing equal frequency Bessel beams: Frozen Waves,” *Optics Express* **12**, 4001-4006 (2004).
- [13] M. Zamboni-Rached, E. Recami and H. E. Hernández-Figueroa “Theory of Frozen Waves: Modelling the Shape of Stationary Wave Fields,” *J. Opt. Soc. Am., A*, (to be published).